

Smart Integration Device License Transfer Guide



It is the reader's responsibility when discussing the information contained this document to maintain a level of confidentiality that is in the best interest of Ricoh USA INC and its member companies.

NO PART OF THIS DOCUMENT MAY BE REPRODUCED IN ANY FASHION AND/OR DISTRIBUTED WITHOUT THE PRIOR PERMISSION OF RICOH USA INC

All product names, partner's brands and their products, domain names or product illustrations, including desktop images used in this document are trademarks, registered trademarks or the property of their respective holders and should be noted as such.

Any trademark or registered trademark found in this support manual is used in an informational or editorial fashion only and for the benefit of such companies. No such use, or the use of any trade name, or web site is intended to convey endorsement or other affiliation with Ricoh products.

Copyright © 2024-2026 Ricoh USA INC

Table of Contents

Table of Contents	4
1 Introduction.....	5
2 Deregister Device	6
Deregistering a device from MFP Operation Panel.....	6
Deregistering a device from RICOH Smart Integration Workplace	8
3 Register a New Device	10
4 Transferring Device Enhancement License.....	12

1 Introduction

This guide provides steps required to transfer RSI Device License to a new device.

Prerequisites: RICOH Smart Integration Administrator Credentials.

Step 1: Deregister device which has RICOH Smart Integration License.

Step 2: Register new device with RICOH Smart integration.


Note: The operation panel screen shot images and RICOH Smart Integration User Site images provided in this document are for illustrative purposes only. These images may not reflect the exact image you experience on your multi-functional printer (MFP device).

2 Deregister Device


Device can be deregistered from MFP Operation Panel or from RICOH Smart Integration Workplace

Deregistering a device from MFP Operation Panel


Step 1: Login to RICOH Smart Integration with Administrator Credentials




Step 2: Enter Administrator credentials to Login,

A screenshot of the RICOH Smart Integration login form. At the top left, there is a back arrow icon and the text "Login to RICOH Smart Integration". Below this, there is a dropdown menu labeled "Login with Email Address". The form contains two input fields: "Email Address" with the text "user @gmail.com" and "Password" which is currently empty. Below the password field, there is a checkbox labeled "Show password". At the bottom right, there is a "Login" button.

Step 3: Select 'Admin Menu'



Step 4: Touch on 'Delete Device Information' to deregister the device.




Deregistering a device from RICOH Smart Integration Workplace

Login to RICOH Smart Integration Workplace with Administrator Credentials from a PC Browser.

URL: <https://na.accounts.ricoh.com/portal/login.html>

Turn on 'Admin Mode'



Click on 'App Usage Permission Management(Devices)'. This will display a list of devices associated with this RICOH Smart Integration Tenant.

Serial Number	Device Enhancement Add-On	ISS Test Package_OLD	RICOH Intelligent Voice Control	Smart Integration Essentials
No. of registered devices 14	7 / 100	7 / 100	0 / 100	1 / 100
G444PB17013 (Multifunction...)				
3120000014 (Multifunctio...)				
C507PC05472 (Multifunctio...)				
C497P600814 (Multifunctio...)	✓			
Y247M410041 (Multifunctio...)				
G135PB00713 (Multifunctio...)		✓		
3129M240898 (Multifunctio...)	✓	✓		
3F43-110519 (Multifunctio...)				
Q Test				

Click on the device, which needs to be deregistered.

Back

Edit Devices

G444PB17013 (Multifunction Printers/Copiers)

Cancel device registration

Information

Save


Back

Copyright © 2019 Ricoh Company, Ltd. All rights reserved.


Click on 'Cancel device registration' to deregister the device.

3 Register a New Device

After deregistering the device as explained in the previous section, a new device can be registered to RICOH Smart Integration to use the license.



Touch on RSI ICON



Touch on the 'Login' button.

Tenant Activation Login

Login with Email Address

Email Address	user@example.com
Password	







Show password

Login

Login with RICOH Smart Integration Administrator Credentials.

Smart Integration Connectors

Login

Scan to CloudFax 	Print from Egnyte 	Scan to Google Shared 
Scan to Box 	Scan to Dropbox 	Scan to Google 
Scan to OneDrive	Scan to OneDrive for	Scan to eFax

This completes device registration.

4 Transferring Device Enhancement License

Refer to 'Device Enhancement Deployment Guide' list on this site:

<https://help-us.na.smart-integration.ricoh.com/user-guides.html>

Step 1: Uninstall Device Enhancement from MFP from which license to be transferred.

Follow Uninstallation steps described in 'Device Enhancement Deployment Guide'.

Step 2: Install Device Enhancement on a New Device.

Follow installation steps in the above guide.